

## 12 mm Wedge Transponder Digital Signature (DST)



### Specifications:

Part Number	RI-TRP-B9WK-xx (xx= see REV table below)			
Functionality	Encryption			
Memory	88 bits			
Memory: Page 1	8 bits Password (user programmable and lockable)			
Page 2	8 bits Identification "ID" (user programmable and lockable)			
Page 3	32 bits Serial Number and Manufacturing Code (Factory programmed and locked)			
Page 4	40 bits Encryption Key (user programmable and lockable)			
Challenge	40 bits (random)			
Response	24 bits + 24 bits of SN with Cyclic Redundancy Check (CRC) on data			
Operating Frequency	134.2 kHz			
Modulation	FSK (Frequency Shift Keying) 134.2 kHz / 123.2 kHz			
Transmission Principle	HDX (Half Duplex)			
Power Source	Powered from the reader signal (batteryless)			
Typical Reading Range	≤ 20 cm **			
Typical Read Time	< 120 ms			
Reading Activation Field Strength @ 25 °C	132.5 dBμA / m			
Operating Temperature (Read)	-40 to +85°C			
Storage Temperature	-40 to +100°C (+175°C for 5 minutes)			
Case Material	Plastic			
Protection Class	IP 68			
EMC	Programmed code is not affected by normal electromagnetic interference or x-rays			
Signal Penetration	Transponder can be read through virtually all non-metallic material			
Mechanical Shock	IEC 68-2-27, Test Ea; 200 g, half sine, 3 ms, 6 shocks per axis			
Vibration	IEC 68-2-6, Test Fc; 10 - 500 Hz, 1.65 mm peak to peak, 10 g, 4 hours per axis			
Dimensions	12.0 mm + 0.2 mm * 6.0 mm + 0.2 mm * 3.0 mm ± 0.05 mm			
Weight	0.4 g			
Packaging	Bulk (2000 units / Box)			
<b>REV.</b>	<b>MFC</b>	<b>Serial Number ( Hex )</b>	<b>From</b>	<b>To</b>
05	10, 11, 12, 13, 14		000000	FFFFFF

\*\* Depending on RF regulation in country of use, the Reader Antenna configuration used, and the environmental conditions.

For more information, contact the sales office or distributor nearest you. This contact information can be found on our web site at: <http://www.ti-rfid.com>

*Texas Instruments reserves the right to change its products and services at any time without notice. TI provides customer assistance in various technical areas, but does not have full access to data concerning the uses and applications of customers products. Therefore, TI assumes no responsibility for customer product design or for infringement of patents and/or the rights of third parties, which may result from assistance provided by TI.*