

date 10/15/2014

page 1 of 3

MODEL: PJ-054H | **DESCRIPTION:** DC POWER JACK

FEATURES

- 5.0 A rating
- 1.65mm center pin
- through hole mount
- vertical orientation





SPECIFICATIONS

parameter	conditions/description	min	typ	max	units
rated input voltage			16		Vdc
rated input current				5	А
contact resistance ¹	between terminal and mating plug between terminal in a closed circuit			50 30	$m\Omega$
insulation resistance	at 500 Vdc	100			МΩ
voltage withstand	at 50/60Hz for 1 minute			500	Vac
insertion/withdrawal force		0.3		3	kg
terminal strength	any direction for 10 seconds			500	g
operating temperature		-25		85	°C
life			5,000		cycles
flammability rating	UL94V-0				
RoHS	2011/65/EU				


Note: 1. When measured at a current of less than 100 mA/1 kHz

SOLDERABILITY


parameter	conditions/description	min	typ	max	units
wave soldering	dipped in solder pot for 5 ±0.5 seconds	255	260	265	°C


MECHANICAL DRAWING


units: mm tolerance: $X.X \pm 0.2mm$ $X.XX \pm 0.1mm$ $X.XXX \pm 0.05mm$





	MATERIAL	PLATING
center pin	copper	nickel
terminal 1	brass	silver
terminal 2	copper alloy	silver
terminal 3	brass	silver
plastic	PA66	
	-	














MATING PLUG Jack Insertion Depth: 6.2 mm

SCHEMATIC	-1 -3 -2
Model	PJ-054H
Center Pin	1.65 mm

REVISION HISTORY

rev.	description	date
1.0	initial release	10/15/2014

The revision history provided is for informational purposes only and is believed to be accurate.



Headquarters 20050 SW 112th Ave. Tualatin, OR 97062 800.275.4899

Fax 503.612.2383 cui.com techsupport@cui.com

CUI offers a one (1) year limited warranty. Complete warranty information is listed on our website.

CUI reserves the right to make changes to the product at any time without notice. Information provided by CUI is believed to be accurate and reliable. However, no responsibility is assumed by CUI for its use, nor for any infringements of patents or other rights of third parties which may result from its use.