



# N-Channel Enhancement-Mode Vertical DMOS FETs

#### **Features**

- ► Free from secondary breakdown
- ► Low power drive requirement
- Ease of paralleling
- ► Low C<sub>ISS</sub> and fast switching speeds
- Excellent thermal stability
- ► Integral source-drain diode
- ► High input impedance and high gain

## **Applications**

- Motor controls
- Converters
- Amplifiers
- Switches
- Power supply circuits
- Drivers (relays, hammers, solenoids, lamps, memories, displays, bipolar transistors, etc.)

#### **General Description**

The Supertex VN2222LL is an enhancement-mode (normally-off) transistor that utilizes a vertical DMOS structure and Supertex's well-proven silicon-gate manufacturing process. This combination produces a device with the power handling capabilities of bipolar transistors, and the high input impedance and positive temperature coefficient inherent in MOS devices. Characteristic of all MOS structures, this device is free from thermal runaway and thermally-induced secondary breakdown.

Supertex's vertical DMOS FETs are ideally suited to a wide range of switching and amplifying applications where very low threshold voltage, high breakdown voltage, high input impedance, low input capacitance, and fast switching speeds are desired.

## **Ordering Information**

Device	Package Option	BV <sub>DSS</sub> /BV <sub>DGS</sub>	R <sub>DS(ON)</sub> (max)	l <sub>D(ON)</sub> (min) (mA)	
	TO-92	(V)	(Παχ) (Ω)		
VN2222	VN2222LL-G	60	7.5	750	

-G indicates package is RoHS compliant ('Green')





## **Absolute Maximum Ratings**

<b>-</b>	
Parameter	Value
Drain-to-source voltage	BV <sub>DSS</sub>
Drain-to-gate voltage	BV <sub>DGS</sub>
Gate-to-source voltage	±30V
Operating and storage temperature	-55°C to +150°C
Soldering temperature*	+300°C

Absolute Maximum Ratings are those values beyond which damage to the device may occur. Functional operation under these conditions is not implied. Continuous operation of the device at the absolute rating level may affect device reliability. All voltages are referenced to device ground.

## **Pin Configuration**



TO-92 (LL)

## **Product Marking**

Si VN 2222L LYYWW

YY = Year Sealed WW = Week Sealed \_\_\_\_ = "Green" Packaging

Package may or may not include the following marks: Si or

TO-92 (LL)

<sup>\*</sup> Distance of 1.6mm from case for 10 seconds.

#### **Thermal Characteristics**

Package	I <sub>D</sub> (continuous) <sup>†</sup> (A)	I <sub>D</sub> (pulsed) (A)	Power Dissipation @T <sub>c</sub> = 25°C (W)	θ <sub>jc</sub> (°C/W)	θ <sub>ja</sub> (°C/W)	Ι <sub>DR</sub> <sup>†</sup> (A)	I <sub>DRM</sub> (A)
TO-92	0.23	1.0	1.0	125	170	0.23	1.0

#### Notes:


# **Electrical Characteristics** (T<sub>A</sub> = 25°C unless otherwise specified)


Sym	Parameter	Min	Тур	Max	Units	Conditions	
BV <sub>DSS</sub>	Drain-to-source breakdown voltage	60	-	-	V	V <sub>GS</sub> = 0V, I <sub>D</sub> = 100μA	
$V_{GS(th)}$	Gate threshold voltage	0.6	-	2.5	V	$V_{GS} = V_{DS}$ , $I_{D} = 1.0 \text{mA}$	
I <sub>GSS</sub>	Gate body leakage current	-	-	100	nA	$V_{GS} = \pm 20V, V_{DS} = 0V$	
		-	-	10		$V_{GS} = 0V, V_{DS} = Max Rating$	
I <sub>DSS</sub>	Zero gate voltage drain current	-	-	500	μA	$V_{GS} = 0V, V_{DS} = 48V,$ $T_{A} = 125^{\circ}C$	
I <sub>D(ON)</sub>	On-state drain current	0.75	-	-	Α	V <sub>GS</sub> = 10V, V <sub>DS</sub> = 10V	
В	Ctatic drain to accuracy an atota registance	-	-	7.5	Ω	V <sub>GS</sub> = 5.0V, I <sub>D</sub> = 200mA	
R <sub>DS(ON)</sub>	Static drain-to-source on-state resistance	-	-	7.5		V <sub>GS</sub> = 10V, I <sub>D</sub> = 500mA	
G <sub>FS</sub>	Forward transconductance	100	-	-	mmho	$V_{DS} = 10V, I_{D} = 500 \text{mA}$	
C <sub>ISS</sub>	Input capacitance	-	-	60		V <sub>GS</sub> = 0V,	
C <sub>oss</sub>	Common source output capacitance	-	-	25	pF	$V_{DS}^{GS} = 25V,$	
C <sub>RSS</sub>	Reverse transfer capacitance	-	-	8.0		f = 1.0MHz	
t <sub>(ON)</sub>	Turn-on time	-	-	10	ne	$V_{DD} = 15V, I_{D} = 0.6A,$	
t <sub>(OFF)</sub>	Turn-off time	-	-	10	ns	$R_{GEN}^{SS} = 25\Omega$	
$V_{SD}$	Diode forward voltage drop	-	0.85	-	V	$V_{GS} = 0V, I_{SD} = 0.2A$	

#### Notes:

- 1. All D.C. parameters 100% tested at 25°C unless otherwise stated. (Pulse test: 300µs pulse, 2% duty cycle.)
- 2. All A.C. parameters sample tested.


## **Switching Waveforms and Test Circuit**






<sup>†</sup>  $I_D$  (continuous) is limited by max rated  $T_i$ .


# 3-Lead TO-92 Package Outline (LL)





**Front View** 

**Side View** 



Symbol		Α	b	С	D	E	E1	е	e1	L
Dimensions (inches)	MIN	.170	.014 <sup>†</sup>	.014 <sup>†</sup>	.175	.125	.080	.095	.045	.500
	NOM	-	-	-	-	-	-	-	-	-
	MAX	.210	.022 <sup>†</sup>	.022 <sup>†</sup>	.205	.165	.105	.105	.055	.610*

JEDEC Registration TO-92.

Drawings not to scale.

Supertex Doc.#: DSPD-3TO92N3, Version E041009.

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information go to <a href="http://www.supertex.com/packaging.html">http://www.supertex.com/packaging.html</a>.)

Supertex inc. does not recommend the use of its products in life support applications, and will not knowingly sell them for use in such applications unless it receives an adequate "product liability indemnification insurance agreement." Supertex inc. does not assume responsibility for use of devices described, and limits its liability to the replacement of the devices determined defective due to workmanship. No responsibility is assumed for possible omissions and inaccuracies. Circuitry and specifications are subject to change without notice. For the latest product specifications refer to the Supertex inc. website: http://www.supertex.com.

©2009 Supertex inc. All rights reserved. Unauthorized use or reproduction is prohibited.



<sup>\*</sup> This dimension is not specified in the JEDEC drawing.

<sup>†</sup> This dimension differs from the JEDEC drawing.